

SM2-L DVR / IP Camera Microphone Interface Adapter with Volume Control

Description

Powers an SM1 series microphone and routes its audio output to an RCA jack (or 3.5mm) for connection to equipment with a un-balanced line level input. For use with DRVs, I/P cameras, remote monitoring applications, and CCTV monitors with built in speakers. Ideal for use with any SM1-X microphone and I/P camera "microphone level" inputs.



Includes

- SM2-L Interface adapter.
- 12 VDC AC adapter.
- 1 each 3' RCA or 3.5mm patch cable.
- Installation instructions.

Options

SPECIFY: RCA OR 3.5mm output connector.

Wiring Requirements

 Microphone cable run: Stranded 22gauge, 2-conductor shielded cable. Distances up to 1500 feet.

Warranty: 1 year parts and labor. Made in USA

SM2-L Interface Adapter Specifications

- RCA or 3.5mm output connector (specify upon ordering).
- Euro-style connectors makes cable terminations fast and clean.
- Adjustable audio output level control.
- Power: 12VDC @ 10ma.
- Reverse polarity protected and fused.
- Dimensions: L 2.7 x W 1.7 x H 1.6

Caution

It is the responsibility of the installation company and end user to comply with state and federal privacy laws regarding the use of audio surveillance equipment. If you are unfamiliar with these laws, consult a qualified attorney. In most cases, posting the provided warning labels in plain view is all that is required.